

UL Short Circuit Rating of Open Components for use in Industrial Control Panels									
Product Group	Frame Size	Description	Fuse Class	Catalog No.	Ampere Rating	Max. 3 Ph. Horsepower Ratings			Standard Fault Short Circuit Current Rating
						240V	480V	600V	
C362	M	Non-fusible rotary switch - base mounted	-	C362NM16	16	2	7.5	7.5	5kA when protected by 30 A. RK5 fuses
				C362NM20	20	3	7.5	10	
				C362NM25	25	5	10	15	
C362	M	Non-fusible rotary switch - back/door mounted	-	C362NM16D	16	2	7.5	7.5	5kA when protected by 30 A. RK5 fuses
				C362NM20D	20	3	7.5	10	
				C362NM25D	25	5	10	15	
C362 / C462	R	Non-fusible rotary switch - base mounted	-	C362NR30	30	7.5	15	25	10kA when protected by 80A. RK5 fuses.
				C462NR30	30	7.5	15	25	
				C362NR40	40	10	20	30	
				C462NR40	40	10	20	30	
	W			C362NW60	60	15	30	40	10kA when protected by 150A. RK5 fuses.
				C362NW80	80	20	40	50	
				C362NW100	100	25	50	60	
C362 / C462	R	Non-fusible toggle switch - base mounted	-	C362TR30	30	7.5	15	25	10kA when protected by 80A. RK5 fuses.
				C462TR30	30	7.5	15	25	
				C362TR40	40	10	20	30	
				C462TR40	40	10	20	30	
	W			C362TW60	60	15	30	40	10kA when protected by 150A. RK5 fuses.
				C362TW80	80	20	40	50	
				C362TW100	100	25	50	60	
C362	C	Non-fusible rotary switch - base mounted	-	C362UC30	30	7.5	15	20	50kA when protected by 30A. CC or J fuses.
				C362UV60	60	15	30	50	
	V	Non-fusible rotary switch - base mounted		C362UV100	100	30	60	75	200kA when protected by 200 A. J fuses
				C362UV200	200	60	125	150	
				C362US400	400	125	250	350	
				C362US600	600	200	400	350	
				C362US800	800	250	500	500	
S	Non-fusible rotary switch - base mounted	C362US1000	1000	250	500	500	100kA when protected by 800A. L fuses		
		C362US1000	1000	250	500	500	100kA when protected by 1000A. L fuses		
		C362US1200	1200	250	500	500	100kA when protected by 1200A. L fuses		
C363	C	Fusible switch - base mounted	CC	C363UC30CT	30	7.5	15	20	50kA with 30A. CC fuses
			J	C363UC30JT	30	7.5	15	20	50kA with 30A. J fuses
C363	V	Fusible switch - base mounted	CC	C363UV30C	30	7.5	15	20	100kA with 30A. CC fuses
			J	C363UV30J	30	7.5	15	20	200kA with 30A. J fuses
			J	C363UV60J	60	15	30	50	200kA with 60A. J fuses
			J	C363UV100J	100	30	60	75	200kA with 100A. J fuses
			J	C363UV200J	200	60	125	150	200kA with 200A. J fuses
			J	C363UV400J	400	125	250	350	200kA with 400A. J fuses
			J	C363UV30CT	30	7.5	15	20	100kA with 30A. CC fuses
			J	C363UV30JT	30	7.5	15	20	200kA with 30A. J fuses
			J	C363UV60JT	60	15	30	50	200kA with 60A. J fuses
			J	C363UV100JT	100	30	60	75	200kA with 100A. J fuses
			J	C363UV200JT	200	60	125	150	200kA with 200A. J fuses

C363	F	Fusible switch - base mounted	J	C363UV400JT	400	125	250	350	200kA with 400A. J fuses
			J	C363UF600J	600	250	500	500	200kA with 600A. J fuse
			L	C363UF800L	800	250	500	500	100kA with 800A. J fuse